

a global revolution in drives...

wireless control for
hundreds of applications



Invertek Drives Ltd.
Offa's Dyke Business Park,
Welshpool,
Powys. SY21 8JF
United Kingdom

with Invertek Drives
the revolution starts here!



Invertek Drives Ltd adopts a policy of continuous improvement and whilst every effort has been made to provide accurate and up to date information, the information contained in this brochure should be used for guidance purposes only and does not form the part of any contract.

Phone: +44 (0) 1938 55 68 68 Fax: +44 (0) 1938 55 68 69
e-mail: sales@invertek.co.uk web: www.invertek.co.uk



User Guide

INVERTEK OPTIDRIVE VTC

Variable Torque Control

AC Variable Speed Drive 1.5 - 160kW



Installation and operating instructions



Declaration of Conformity:

Invertek Drives Ltd hereby states that the Optidrive VTC product range is CE marked for the low voltage directive and conforms to the following harmonised European directives :

- EN 61800-5-1 : Adjustable speed electrical power drive systems
- EN 61800-3 : Adjustable Speed Electrical Power Drive Systems – Part 3 (EMC)
- EN 55011 : Limits and Methods of measurement of radio interference characteristics of Industrial Equipment (EMC)

CE - Konformitätserklärung:

gemäß den Produktnormen für Drehzahlveränderbare Antriebe

Die Firma 'Invertek Drives Ltd., UK erklärt dass das Produkt: Optidrive VTC (statischer Frequenzumrichter zur Drehzahlregelung von Asynchronmotoren) nach den folgenden harmonisierten Produktnormen entwickelt und gebaut wird:

- EN 61800-5-1 : Elektrische Leistungsantriebssysteme mit einstellbarer Drehzahl
- EN 61800-3 : Drehzahlveränderbare elektrische Antriebe – Teil 3 (EMV)
- EN 55011 : Funkstörungen - Grenzwerte und Messverfahren (EMV)

Déclaration de Conformité:

Invertek Drives Ltd déclare par la présente que le produit Optidrive VTC porte le marquage CE en relation avec la directive basse tension et est conforme aux norms Européennes harmonisées suivantes :

- EN 61800-5-1 : Equipement électronique utilisé dans les installations de puissance
- EN 61800-3 : Entraînements électriques de puissance à vitesse variable - Partie 3
- EN 55011 : Normes génériques / Compatibilité électromagnétique (CEM)

SIZE 5 (INTEGRAL RFI FILTER, LINE CHOKE & BRAKING TRANSISTOR)

Model	ODV-xxxx-zz ¹⁾	52300	52370	52450
Motor output rating – VTC 110% o/l	kW	30	37	45
Model	ODV-xxxx-USA	52400	52500	52600
Motor output rating – VTC 110% o/l	HP	40	50	60
Supply voltage / phases	V±10%	220-240 / 1Ø (with 50% derating) or 3Ø		
Supply fuse or MCB (type B) ²⁾	A	200	250-300	250-300
Output voltage / phases	V	0-240 / 3Ø		
Output Amps – VTC 110% overload	A	110	150	180
Motor cable size, Copper 75 °C	mm ²	35	55	70
Max motor cable length	m	100		
Min brake resistor	Ω	3		

Model	ODV-xxxx-zz ¹⁾	54550	54750	54900
Motor output rating – VTC 110% o/l	kW	55	75	90
Model	ODV-xxxx-USA	54750	54100	54120
Motor output rating – VTC 110% o/l	HP	75	100	120
Supply voltage / phases	V±10%	380-480 / 1Ø (with 50% derating) or 3Ø		
Supply fuse or MCB (type B) ²⁾	A	200	250-300	250-300
Output voltage / phases	V	0-480 / 3Ø		
Output Amps – VTC 110% overload	A	110	150	180
Motor cable size, Copper 75 °C	mm ²	35	55	70
Max motor cable length	m	100		
Min brake resistor	Ω	6		

SIZE 6 (EXTERNAL LINE CHOKE, INTEGRAL RFI FILTER & BRAKING TRANSISTOR)

Model	ODV-xxxx-zz ¹⁾	64110	64132	64160
Motor output rating – VTC 110% o/l	kW	110	132	160
Model	ODV-xxxx-USA	64150	64175	64210
Motor output rating – VTC 110% o/l	HP	150	175	210
Supply voltage / phases	V±10%	380-480 / 1Ø (with 50% derating) or 3Ø		
Supply fuse or MCB (type B) ²⁾	A	315	350	400
Output voltage / phases	V	0-480 / 3Ø		
Output Amps – VTC 110% overload	A	202	240	300
Motor cable size, Copper 75 °C	mm ²	90	120	170
Max motor cable length	m	100		
Min brake resistor	Ω	6		

1) "-zz" in the part number refers to the country variation

2) For cUL compliance, use fuse type Bussmann KTN-R / KTS-R or equivalent

Maximum supply ratings for UL compliance :

Drive rating	Maximum supply voltage	Maximum short circuit current
230V ratings 0.37kW (0.5HP) to 18.5kW (22HP)	240V rms (AC)	5kA rms (AC)
230V ratings 22kW (30HP) to 90kW (120HP)	240V rms (AC)	10kA rms (AC)
400/460V/600V ratings 0.75kW (1HP) to 37kW (50HP)	500V/600Vrms (AC)	5kA rms (AC)
400/460V/600V ratings 45kW (60HP) to 160kW (250HP)	500V/600V rms (AC)	10kA rms (AC)

All the drives in the above table are suitable for use on a circuit capable of delivering not more than the above specified maximum short-circuit Amperes symmetrical with the specified maximum supply voltage.

Rev. 2.21

Invertek Drives Ltd adopts a policy of continuous improvement and whilst every effort has been made to provide accurate and up to date information, the information contained in this brochure should be used for guidance purposes only and does not form the part of any contract.

SIZE 3 (INTEGRAL RFI FILTER, INTEGRAL DC LINK CHOKE & BRAKING TRANSISTOR)

Model	ODP-xxxx-zz ¹⁾	35075	35110	35150 **
Motor output rating – VTC 110% o/l	kW	7.5	11.0	15.0
Model	ODP-xxxx-USA	35100	35150	35200 **
Motor output rating – VTC 110% o/l	HP	10	15	20
Supply voltage / phases	V±10%	500-600 / 1Ø (with 50% derating) or 3Ø		
Supply fuse or MCB (type B) ²⁾	A	32	32	50
Output voltage / phases	V	0-575V / 3Ø		
Output Amps – VTC 110% overload	A	14	18	24
Motor cable size, Copper 75 °C	mm ²	2.5		4
Max motor cable length	m	100		
Min brake resistor	Ω	22		

* Maximum rating for UL applications ** Models not UL listed

- 1) “-zz” in the part number refers to the country variation
 2) For cUL compliance, use fuse type Bussmann KTN-R / KTS-R or equivalent

SIZE 4 (INTEGRAL RFI FILTER, LINE CHOKE & BRAKING TRANSISTOR)

Model	ODV-xxxx-zz ¹⁾	42075	42110	42150	42185	42220
Motor output rating – VTC 110% o/l	kW	7.5	11	15	18.5	22
Model	ODV-xxxx-USA	42100	42150	42200	42250	42300
Motor output rating – VTC 110% o/l	HP	10	15	20	25	30
Supply voltage / phases	V±10%	220-240 / 1Ø (with 50% derating) or 3Ø				
Supply fuse or MCB (type B) ²⁾	A	80	80-100	100	100-125	160
Output voltage / phases	V	0-240 / 3Ø				
Output Amps – VTC 110% overload	A	39	46	61	72	90
Motor cable size, Copper 75 °C	mm ²	10	10	16	16	25
Max motor cable length	m	100				
Min brake resistor	Ω	6				
Model	ODV-xxxx-zz ¹⁾	44185	44220	44300	44370	44450
Motor output rating – VTC 110% o/l	kW	18.5	22	30	37	45
Model	ODV-xxxx-USA	44250	44300	44400	44500	44600
Motor output rating – VTC 110% o/l	HP	25	30	40	50	60
Supply voltage / phases	V±10%	380-480 / 1Ø (with 50% derating) or 3Ø				
Supply fuse or MCB (type B) ²⁾	A	80	80-100	100	100-125	160
Output voltage / phases	V	0-480 / 3Ø				
Output Amps – VTC 110% overload	A	39	46	61	72	90
Motor cable size, Copper 75 °C	mm ²	10	10	16	16	25
Max motor cable length	m	100				
Min brake resistor	Ω	12				

- 1) “-zz” in the part number refers to the country variation
 2) For cUL compliance, use fuse type Bussmann KTN-R / KTS-R or equivalent

CONTENTS

	Page
1. General	4
1.1 Important safety information	4
1.2 Electromagnetic Compatibility (EMC)	4
2. Mechanical Installation	5
2.1 General	5
2.2 Mechanical dimensions and mounting	5
2.3 Enclosure mounting	6
3. Electrical Installation	7
3.1 Safety	7
3.2 Precautions	7
3.3 Drive and motor connection	8
3.4 Control terminal connections	9
4. Operation	10
4.1 Managing the keypad	10
4.2 Easy startup	10
5. Configuration	11
5.1 Basic parameters	11
5.2 Extended parameters	12
5.3 User Feedback control	15
5.4 High performance Motor control	15
5.5 Digital input configuration – terminal mode	16
5.6 Digital input configuration – keypad mode	17
5.7 Digital input configuration – User PID mode	17
5.8 Digital input configuration – Modbus control mode	18
5.9 Real-time monitoring parameters	18
6. Troubleshooting	19
6.1 Fault finding chart	19
6.2 Fault messages	19
6.3 Auto-tune trouble shooting	20
7. Technical data	20
7.1 User interface	20
7.2 Power stage protection	20
7.3 Environmental	20
7.4 Rating tables	21

All rights reserved. No part of this User Guide may be reproduced or transmitted in any form or by any means, electrical or mechanical including photocopying, recording or by any information storage or retrieval system without permission in writing from the publisher.

Copyright Invertek Drives Ltd © 2006

The manufacturer accepts no liability for any consequences resulting from inappropriate, negligent or incorrect installation, or adjustment of the optional operating parameters of the drive or from mismatching of the drive to the motor.

The contents of this User Guide are believed to be correct at the time of printing. In the interests of a commitment to a policy of continuous improvement, the manufacturer reserves the right to change the specification of the product or its performance or the contents of the User Guide without notice.

All Invertek drives products carry a 2-year warranty, valid from the date of manufacture. This data is clearly visible on the rating label.

1. General

1.1 Important safety information



This variable speed drive product (Optidrive) is intended for professional incorporation into complete equipment or systems. If installed incorrectly it may present a safety hazard. The Optidrive uses high voltages and currents, carries a high level of stored electrical energy, and is used to control mechanical plant that may cause injury. Close attention is required to system design and electrical installation to avoid hazards in either normal operation or in the event of equipment malfunction.

System design, installation, commissioning and maintenance must be carried out only by personnel who have the necessary training and experience. They must carefully read this safety information and the instructions in this Guide and follow all information regarding transport, storage, installation and use of the Optidrive, including the specified environmental limitations.

Please read the IMPORTANT SAFETY INFORMATION below, and all Warning and Caution information elsewhere.

Safety of machinery, and safety-critical applications



The level of integrity offered by the Optidrive control functions – for example stop/start, forward/reverse and maximum speed, is not sufficient for use in safety-critical applications without independent channels of protection. All applications where malfunction could cause injury or loss of life must be subject to a risk assessment and further protection provided where needed. Within the European Union, all machinery in which this product is used must comply with Directive 89/392/EEC, Safety of Machinery. In particular, the electrical equipment should comply with EN60204-1.

1.2 Electromagnetic compatibility (EMC)

Optidrive is designed to high standards of EMC. EMC data is provided in a separate EMC Data Sheet, available on request. Under extreme conditions, the product might cause or suffer disturbance due to electromagnetic interaction with other equipment. It is the responsibility of the installer to ensure that the equipment or system into which the product is incorporated complies with the EMC legislation of the country of use. Within the European Union, equipment into which this product is incorporated must comply with 89/336/EEC, Electromagnetic Compatibility.

When installed as recommended in this User Guide, the radiated emissions levels of all Optidrives are less than those defined in the Generic radiated emissions standard EN61000-6-4. Every Optidrive has a built-in filter to reduce conducted emissions. The conducted emission levels are less than those defined in the Generic radiated emissions standard EN61000-6-4 (class A) for the following cable lengths :

Optidrive sizes #1 to #3 : up to 5m of screened cable
Optidrive sizes #4 to #6 : up to 25m of screened cable

Optidrive sizes #1 to #3 can be fitted with an optional external Optifilter (HF filter). When correctly fitted with this filter, the conducted emission levels are less than those defined in the Generic radiated emissions standard EN61000-6-3 (class B) for screened cable lengths up to 5m and with EN61000-6-4 (class A) for screened cable lengths up to 25m.

7.4 Drive rating tables

SIZE 2 (INTEGRAL RFI FILTER, INTEGRAL BRAKING TRANSISTOR)

Model	ODV-xxxx-zz ¹⁾	22150	22220
Motor output rating – VTC 110% o/l	kW	1.5	2.2
Model	ODV-xxxx-USA	22020	22030
Motor output rating – VTC 110% o/l	HP	2	3
Supply voltage / phases	V±10%	220-240 / 1Ø or 3Ø ³⁾	
Supply fuse or MCB (type B) ²⁾	A	20	32
Output voltage / phases	V	0-240V / 3Ø	
Output Amps – VTC 110% overload	A	7	10.5 (* 9)
Motor cable size, Copper 75 °C	mm ²	1.5	
Max motor cable length	m	100	
Min brake resistor	Ω	33	22

Model	ODV-xxxx-zz ¹⁾	24150	24220	24400
Motor output rating – VTC 110% o/l	kW	1.5	2.2	4.0
Model	ODV-xxxx-USA	24020	24030	24050
Motor output rating – VTC 110% o/l	HP	2	3	5
Supply voltage / phases	V±10%	380-480 / 1Ø (with 50% derating) or 3Ø		
Supply fuse or MCB (type B) ²⁾	A	10	10	20
Output voltage / phases	V	0-480 / 3Ø		
Output Amps – VTC 110% overload	A	4.1	5.8	9.5
Motor cable size, Copper 75 °C	mm ²	1.0	1.5	
Max motor cable length	m	100		
Min brake resistor	Ω	47	47	33

Model	ODP-xxxx-zz ¹⁾	25150 ⁴⁾	25220 ⁴⁾	25370 ⁴⁾	25550 ⁴⁾
Motor output rating – VTC 110% o/l	kW	1.5	2.2	3.7	5.5
Model	ODP-xxxx-USA	25020 ⁴⁾	25030 ⁴⁾	25050 ⁴⁾	25750 ⁴⁾
Motor output rating – VTC 110% o/l	HP	2	3	5	7.5
Supply voltage / phases	V±10%	500-600 / 1Ø (with 50% derating) or 3Ø			
Supply fuse or MCB (type B) ²⁾	A	10	10	10	20
Output voltage / phases	V	0-575V / 3Ø			
Output Amps – VTC 110% overload	A	3.1	4.1	5.8	9.0
Motor cable size, Copper 75 °C	mm ²	1.0		1.5	
Max motor cable length	m	100	100	100	100
Min brake resistor	Ω	47			

SIZE 3 (INTEGRAL RFI FILTER, INTEGRAL DC LINK CHOKE & BRAKING TRANSISTOR)

Model	ODV-xxxx-zz ¹⁾	32030	32040	32055
Motor output rating – VTC 110% o/l	kW	3.0	4.0	5.5
Model	ODV-xxxx-USA	32040	32050	32075
Motor output rating – VTC 110% o/l	HP	4	5	7.5
Supply voltage / phases	V±10%	220-240 / 1Ø (with 50% derating) or 3Ø		
Supply fuse or MCB (type B) ²⁾	A	32	32	50
Output voltage / phases	V	0-240 / 3Ø		
Output Amps – VTC 110% overload	A	14	18	25 (* 24)
Motor cable size, Copper 75 °C	mm ²	2.5	2.5	4
Max motor cable length	m	100		
Min brake resistor	Ω	15		

Model	ODV-xxxx-zz ¹⁾	34055	34075	34110	34150 **
Motor output rating – VTC 110% o/l	kW	5.5	7.5	11.0	15.0
Model	ODV-xxxx-USA	34075	34100	34150	34200 **
Motor output rating – VTC 110% o/l	HP	7.5	10	15	20
Supply voltage / phases	V±10%	380-480 / 1Ø (with 50% derating) or 3Ø			
Supply fuse or MCB (type B) ²⁾	A	32	32	50	50
Output voltage / phases	V	0-480 / 3Ø			
Output Amps – VTC 110% overload	A	14	18	25 (* 24)	30
Motor cable size, Copper 75 °C	mm ²	2.5	2.5	4	6
Max motor cable length	m	100			
Min brake resistor	Ω	22			

* Maximum rating for UL applications

** Models not UL listed

- 1) "-zz" in the part number refers to the country variation
- 2) For cUL compliance, use fuse type Bussmann KTN-R / KTS-R or equivalent
- 3) Part number for 1-phase supply different to part number for 3-phase supply
- 4) Input Filter must be fitted for all Size 2 575V drive installations.

6.3 Auto-tune trouble shooting

Trip message	Explanation and check point
At-F01	Measured motor stator resistance varies between phases. Ensure that all motor phases are connected to the drive. Check motor for winding imbalance.
At-F02	Measured motor stator resistance is too large. Ensure that motor is connected. Check that the motor power matches the drive power rating.

Notes: Ensure that the correct motor nameplate parameters are entered in P1-07...P1-09 before the Auto-tune is carried out. Ensure that the motor winding (star or delta) connection is correct and that the motor is connected to the drive.

7. Technical data

7.1 User interface

Bipolar Analog Input : (terminal 6)	Resolution = +/-12-bits (0.025%), 8ms sampling time Range settings: 0..10V, 0..24V, -10..10V. Max input voltage 30V DC Input impedance: 22 kOhm
2 nd Analog input : (terminal 4)	Resolution = +11-bits (0.05%), 8ms sampling time Range settings: 0..10V, 4..20mA, 0..20mA. Max input voltage 30V DC Input impedance: 70 kOhm
Digital inputs : (terminals 2, 3, 4)	Positive logic only. Sampling interval : 8ms sampling time "Logic 1" input voltage range: 8V ... 30V DC. "Logic 0" input voltage range: 0 ... 4V DC.
User +24V output : (terminals 1, 5)	Output load regulation +/-0.4% over full load range. Max output current = 100mA total. Short circuit proof.
Analog output : (terminal 8)	Resolution = 8-bits, 16ms update cycle time Output formats: 0..10V, 4..20mA. Max current = 20mA. Short circuit proof.
2 nd digital output : (terminal 3)	PNP output, max output current = 10mA. Short circuit proof.
User relay : (terminals 10, 11)	Contact rating : 250Vac, 6A / 30Vdc, 5A.

7.2 Power stage protection

- Output short-circuit, phase-to-phase, phase-to-earth
- Output over-current. Trip set at 200% of rated drive current
- Overload protection. Drive delivers 110% of rated motor current for 60s
- Braking transistor protected against short-circuit.
- Braking resistor overload (when enabled)
- Over-voltage trip. Set at 123% of drive maximum rated supply voltage
- Under-voltage trip.
- Over temperature trip
- Under temperature trip. (Drive will trip if enabled below 0 °C)
- Supply Phase imbalance. A supply imbalance of >3% persisting for more than 30s will trip a running drive.
- Supply Phase loss. If one phase of a 3-phase supply is lost for more than 15s, a running drive will trip.

7.3 Environmental


Operational ambient temperature range : 0 ... 50 °C
 Storage ambient temperature range : -40 ... 60 °C
 Maximum altitude : 2000m. Derate above 1000m 1% / 100m
 Maximum humidity : 95%, non-condensing

2. Mechanical Installation

2.1 General

- Carefully inspect the Optidrive before installation to ensure it is undamaged
- Store the Optidrive in its box until required. Storage should be clean and dry and within the temperature range -40°C to +60°C
- Install the Optidrive on a flat, vertical, flame-resistant, vibration-free mounting within a suitable enclosure, according to EN60529 if specific Ingress Protection ratings are required
- The Optidrive must be installed in a pollution degree 1 or 2 environment
- Flammable material should not be placed close to the drive
- The entry of conductive or flammable foreign bodies should be prevented
- Max. operational ambient temperature 50°C, min. 0°C. Refer to rating tables in section 7.4
- Relative humidity must be less than 95% (non-condensing)
- Optidrives can be installed side-by-side with their heatsink flanges touching. This gives adequate ventilation space between them. If the Optidrive is to be installed above another drive or any other heat-producing device, the minimum vertical spacing is 150mm. The enclosure should either be force-ventilated or large enough to allow natural cooling (refer to tables in section 2.3 for further information).

2.2 Mechanical dimensions and mounting




	Size 2	Size 3	Size 4	Size 5	Size 6 **
Length / mm	260	260	520	1045	1100
Width / mm	100	171	340	340	340
Depth / mm	175	175	220	220	330
Weight/ kg	2.6	5.3	28	67	55
A / mm	210	210	420	945	945
B / mm	92	163	320	320	320
J / mm	4		9.5		
K / mm	25		50		
Fixings	2 * M4	4 * M4		4 * M8	
Power Terminal torque settings	1 Nm		4 Nm	8 Nm	

** S6 has external line choke, weight 27kg. Dimensions : 280mm x 280mm x 280mm (W x L x D)

2.3 Enclosure mounting and dimensions

For applications that require a higher IP rating than the IP20 offered by the standard drive, the drive must be mounted in a metallic enclosure. The following guidelines should be observed for these applications:

- Enclosures should be made from a thermally conductive material, unless forced ventilation is used.
- When vented enclosures are used, there should be venting above the drive and below the drive to ensure good air circulation. Air should be drawn in below the drive and expelled above the drive.
- If the external environment contains contamination particles (eg dust), a suitable particle filter should be fitted to the vents and forced ventilation implemented. The filter must be serviced / cleaned appropriately.
- High moisture, salt or chemical content environments should use a suitably sealed (non-vented) enclosure.



Non-Vented Metallic Enclosure Dimensions (mm)

Drive Power rating	L	W	D	G
Size 2 1.5kW 230V / 2.2kW 400V	400	300	300	60
Size 2 2.2kW 230V / 4kW 400V	600	450	300	100

Vented Metallic Enclosure Dimensions (mm)

Drive Power rating	Free-Vented unit				Force-vented unit				Air Flow
	L	W	D	G	L	W	D	G	
Size 2 4 kW	600	400	250	100	400	300	250	100	> 45m ³ /h
Size 3 15 kW	800	600	300	150	600	400	250	150	> 80m ³ /h
Size 4 22 kW	1000	600	300	200	800	600	300	200	> 300m ³ /h
Size 4 37 kW	-	-	-	-	800	600	300	200	> 300m ³ /h
Size 5 90 kW	-	-	-	-	1600	800	400	200	> 900m ³ /h
Size 6 160 kW	-	-	-	-	2000	800	400	200	>1000m ³ /h

6. Troubleshooting

6.1 Fault-finding chart

Symptom	Cause and Solution
Overload or over-current trip on unloaded motor during acceleration	Check Star / Delta terminal connection in motor. Rated operating voltage of drive and motor should match. The Delta connection always gives the lower voltage rating of a dual voltage motor
Overload or over-current – motor does not spin	Check for locked rotor. Check that the mechanical brake is released (if fitted)
Drive will not enable – display remains on 'StoP'	Check that the hardware enable signal is applied to digital input 1. Ensure that the User +24V output voltage (between terminals 5 and 7) is correct. If not, check wiring to user terminal strip. Check P1-12 for terminal / keypad mode. If keypad mode selected, press the START button. Check that supply voltage is within specification
In very cold ambient conditions, drive will not power up	If the ambient temperature is less than -10 °C, the drive may not power up. Ensure that a local heating source keeps the ambient above 0 °C in these conditions.
Extended menus cannot be accessed	Ensure that P1-14 is set to the extended access code. This is "101" unless the code in P2-37 has been changed by the user.

6.2 Fault messages

Trip message	Explanation
P-dEF	Default parameters loaded, usually after pressing STOP, UP & DOWN keys for 1s. Press STOP to reset the trip. Display then reads "StoP"
"O-I" "h O-I"	Over-current on drive output to motor. Trip on drive enable : check for wiring error or short circuit Trip on motor starting : check for stalled or jammed motor Trip during operation : check for sudden overload or malfunction If "h O-I" occurs, check for short circuit on output. If wiring correct, contact your supplier.
"I.t-trP"	Drive overload trip, occurring when the drive has been delivering >100% rated current (set in P1-08) for a period of time. The display flashes to indicate an overload condition.
"O-Uolt"	Over-voltage on DC bus. Check supply voltage is within limits. If trip occurs on deceleration, increase deceleration time or fit braking resistor.
"U-Uolt"	Under-voltage trip. Happens routinely when drive powered down. If it occurs whilst running, check supply voltage
"OI-b"	Over current in the brake resistor circuit. Check cabling to brake resistor
"OL-br"	Brake resistor overload. Increase deceleration time, reduce load inertia or add further brake resistors in parallel. Ensure minimum resistance values from ratings tables in section 7.4 are observed.
"O-t"	Over-temperature trip. Check drive cooling and possible enclosure dimensions
"U-t"	Under-temperature trip. Trip occurs if ambient is less than 0 °C. Drive ambient temperature must be raised above zero in order to start the drive.
"th-Flt"	Thermistor hardware fault. Contact your local distributor for further information.
"PS-trP"	Trip on drive enable : check for wiring error or short circuit Trip during operation : check for sudden overload or over-temperature
"dAtA-F"	Occurs routinely after Flash upgrade. Reset using the STOP button or after a power down cycle. All parameters set to default after an upgrade.
"P-LOSS"	Drive intended for use with a 3-phase supply has lost one phase. Condition must persist for >15s before a trip occurs. Phase loss detection disabled if parameters defaulted (P-dEF) when L3 has been removed.
"Ph-Ib"	Phase imbalance. Trips if the phase imbalance exceeds 3%. Condition must persist for >30s before a trip occurs.
"SC-trP"	Check integrity of OptiLink (communication link) between drives interconnected optically. Check that each drive in a network has a unique drive address (P2-27)
"E-triP"	External trip (connected to digital input 3). Check motor thermistor (if connected)
"At-Fxx"	Auto-tune failed to complete successfully. (xx = 01...02) See 6.3 for more details.
"SPIN-F"	Spin start function failed to detect the motor speed. Check cable connection between drive and motor. Make sure that the motor actual speed is less than the maximum speed limit (P1-01). Make sure that the motor base frequency (P1-09) is less than 100Hz.

5.8 Digital input configuration – Fieldbus control mode (P1-12 = 4)

The following table defines the digital input functionality when the drive is in Modbus control mode

P2-01	Digi input 1 function	Digi input 2 function	Digi input 3 function	Analog input function
0..2,4 6..9, 13..16,18	O : Stop (Disable) C : Run (Enable)	No effect	No effect	Not Used
3	O : Stop (Disable) C : Run (Enable)	O : Forward C : Reverse	O : Master speed ref C : Preset speed 1	Not Used
5	O : Stop (Disable) C : Run (Enable)	O : Master speed ref C : Preset speed	Digi input 3	Analog input
			Open	Open
			Closed	Open
			Open	Closed
			Closed	Closed
				Preset value
				Preset speed 1
				Preset speed 2
				Preset speed 3
				Preset speed 4
10	O : Stop (Disable) C : Run (Enable)	O : Master speed ref C : Digital speed ref	External trip input : O : trip C : OK	Not Used
11	O : Stop (Disable) C : Run (Enable)	O : Master speed ref C : Preset speed 1	External trip input : O : trip C : OK	Not Used
12	O : Stop (Disable) C : Run (Enable)	O : Master speed ref C : Bipolar analog input	External trip input : O : trip C : OK	Bipolar analog input
17	O : Stop (Disable) C : Run (Enable)	O : Master speed ref C : Bipolar analog input	No effect	Bipolar analog input
19	O : Stop (Disable) C : Run (Enable)	O : Master speed ref C : 2 nd analog input	2 nd analog input	Not Used
20,21	O : Stop (Disable) C : Run (Enable)	2 nd digital output : Drive healthy = +24V	O : Master speed ref C : Preset speed 1	Not Used
22	O : Stop (Disable) C : Run (Enable)	2 nd digital output : Drive healthy = +24V	External trip input : O : trip C : OK	Not Used
23	O : Stop (Disable) C : Run (Enable)	O : Normal control C : Fire mode	O : Master speed ref C : Preset speed 1	Not Used

Notes: - If P2-19 = 2 or 3, drive can only be started / stopped by closing / opening digital input 1. If P2-19 = 0 or 2, the master speed reference will be automatically reset to zero each time when drive is stopped.
- Digital input 1 must be closed in all cases to enable the drive

5.9 Real-time monitoring parameters

Parameter group zero provides access to internal drive read-only parameters for monitoring purposes.

Par	Description	Display range	Explanation
P0-01	Bipolar analog input value	-100%...100%	100% = max input voltage
P0-02	2 nd analog input value	0..100%	100% = max input voltage
P0-03	Speed controller reference	-500%...500%	100% = Base frequency (P1-09)
P0-04	Digital speed ref (digi pot)	- P1-01 ... P1-01	Speed displayed in Hz / rpm
P0-05	Reserved		
P0-06	User PID ref input	0..100%	PID controller reference value
P0-07	User PID feedback	0..100%	PID controller feedback value
P0-08	User PID error input	0..100%	Reference – Feedback
P0-09	User PID P-term	0..100%	Proportional component
P0-10	User PID I-term	0..100%	Integral component
P0-11	User PID D-term	0..100%	Differential component
P0-12	User PID output	0..100%	Combined output
P0-13	Reserved		
P0-14	Magnetising current	A rms	Magnetising current in A rms
P0-15	Reserved		
P0-16	Field strength	0..100%	Magnetic field strength
P0-17	Stator resistance	Ohm	Phase - Phase stator resistance
P0-18	Reserved		
P0-19	Reserved		
P0-20	DC bus voltage	V dc	Internal DC bus voltage
P0-21	Drive temperature	°C	Internal drive temperature
P0-22	Supply voltage L1 – L2	V rms, ph-ph	Phase – phase supply voltage
P0-23	Supply voltage L2 – L3	V rms, ph-ph	Phase – phase supply voltage
P0-24	Supply voltage L3 – L1	V rms, ph-ph	Phase – phase supply voltage
P0-25	Reserved		
P0-26	kWh meter	0.0 ... 999.9 kWh	Cumulative energy consumption
P0-27	MWh meter	0.0 ... 60000 MWh	Cumulative energy consumption
P0-28	Software ID, IO processor	eg "1.00", "493F"	Version number and checksum
P0-29	Software ID, Motor control	eg "1.00", "7A5C"	Version number and checksum
P0-30	Drive serial number	000000 ... 999999 00-000 ... 99-999	Unique drive serial number eg 540102 / 24 / 003

3. Electrical Installation

3.1 Safety



Electric shock hazard! Disconnect and **ISOLATE** the Optidrive before attempting any work on it. High voltages are present at the terminals and within the drive for up to 10 minutes after disconnection of the electrical supply.

- Optidrives should be installed only by qualified electrical persons and in accordance with local and national regulations and codes of practice.
- The Optidrive has an Ingress Protection rating of IP20. For higher IP ratings, use a suitable enclosure.
- Where the electrical supply to the drive is through a plug and socket connector, do not disconnect until 10 minutes have elapsed after turning off the supply
- Ensure correct earthing connections, see diagram below
- The earth cable must be sufficient to carry the maximum supply fault current which normally will be limited by the fuses or MCB

3.2 Precautions

- Ensure that the supply voltage, frequency and number of phases (single or three phase) correspond to the rating of the Optidrive as delivered
- An isolator or similar should be installed between the power supply and the drive
- Never connect the mains power supply to the Optidrive output terminals UVW
- Protect the drive by using slow-blow HRC fuses or an MCB located in the mains supply to the drive
- Do not install any type of automatic switchgear between the drive and the motor
- Wherever control cabling is close to power cabling, maintain a minimum separation of 100 mm and arrange crossings at 90°
- Ensure that screening or armouring of power cables is effected in accordance with the connections diagram below
- Ensure that all terminals are tightened to the appropriate torque (see table, left)


Connect drive according to the following diagram, ensuring that motor terminal box connections are correct. There are two connections in general : Star and Delta. It is essential to ensure that the motor is connected in accordance with the voltage at which it will be operated. For more information, refer to the following diagram

For recommended cabling and wiring sizing, refer to section 7.4.

It is recommended that the power cabling should be 3-core or 4-core PVC-insulated screened cable, laid in accordance with local industrial regulations and codes of practice.

The ground terminal of each Optidrive should be individually connected DIRECTLY to the site earth (ground) bus-bar (through the filter if installed) as shown. Optidrive ground connections should not loop from one drive to another, or to, or from any other equipment. Ground loop impedance must conform to local industrial safety regulations. To meet UL regulations, UL approved ring crimp terminals should be used for all earth wiring connections.

3.3 Drive and motor connection



* If fitted, a filter should be mounted physically close to the Drive. For maximum effectiveness, the metal case of the filter and the heat sink of the drive should be electrically connected, ie screw both to a metal back plate and ensure metal-to-metal contact.

Motor terminal box connections

Most general purpose motors are wound for operation on dual voltage supplies. This is indicated on the nameplate of the motor

This operational voltage is normally selected when installing the motor by selecting either STAR or DELTA connection.


STAR always gives the higher of the two voltage ratings.

Typical ratings are :



400 / 230 (Δ / Δ)

690 / 400 (Δ / Δ)

DELTA (Δ) Connection



STAR (Δ) Connection



5.6 Digital input configuration – keypad mode (P1-12 = 1 or 2)

The following table defines the function of the digital inputs in keypad mode (set using P1-12).

P2-01	Digi input 1 function	Digi input 2 function	Digi input 3 function	Analog input function	
0 ¹⁾	O : Stop (Disable) C : Run (Enable)	Closed : Remote pushbutton UP	Closed : Remote pushbutton DOWN	When drive is stopped, closing digital inputs 2 & 3 together starts drive. Bipolar analog input has no effect	
1	O : Stop (Disable) C : Run (Enable)	Closed : Remote pushbutton UP	External trip input : O : Trip C : OK	Closed : Remote pushbutton DOWN	
2	O : Stop (Disable) C : Run (Enable)	Closed : Remote pushbutton UP	O : Digital speed ref C : Preset speed 1	Bipolar analog input > 5V reverses rotation	
3...9, 13,14, 16	O : Stop (Disable) C : Run (Enable)	Closed : Remote pushbutton UP	Closed : Remote pushbutton DOWN	When drive is stopped, closing digital inputs 2 & 3 together starts the drive. Bipolar analog input > 5V reverses rotation	
10	O : Stop (Disable) C : Run (Enable)	O : Digital speed ref C : Bipolar analog input	External trip input : O : Trip C : OK	Analog speed reference	
11	O : Stop (Disable) C : Run (Enable)	O : Digital speed ref C : Preset speed 1	External trip input : O : trip C : OK	Allows connection of motor thermistor on terminal 4. Bipolar analog input > 5V reverses rotation	
12	O : Stop (Disable) C : Run (Enable)	O : Preset speed 1 C : Digital speed ref	External trip input : O : trip C : OK	Bipolar analog input > 5V reverses rotation	
15	O : Stop (Disable) C : Run (Enable)	O : Digital speed ref C : Preset speed 1	O : Decel ramp 1 C : Decel ramp 2	Bipolar analog input > 5V reverses rotation	
17	O : Stop (Disable) C : Run (Enable)	O : Digital speed ref C : Bipolar analog input	O : Digital / analog speed C : Preset speed 1	Analog speed reference	
18	O : Stop (Disable) C : Run (Enable)	O : Digital speed ref C : Preset speed	Digi input 3	Analog input	Preset value
			Open	Open	Preset speed 1
			Closed	Open	Preset speed 2
			Open	Closed	Preset speed 3
19	O : Stop (Disable) C : Run (Enable)	O : Digital speed ref C : 2 nd analog input	2 nd analog input	Bipolar analog input > 5V reverses rotation	
20,21	O : Stop (Disable) C : Run (Enable)	2 nd digital output : Drive healthy = +24V	O : Digital speed ref C : Preset speed 1		
22	O : Stop (Disable) C : Run (Enable)	2 nd digital output : Drive healthy = +24V	External trip input : O : trip C : OK		
23 ²⁾	O : Stop (Disable) C : Run (Enable)	O : Normal control C : Fire mode	O : Digital speed ref C : Preset speed 1		

Notes:

- 1) In addition to the speed being set using the pushbuttons on the front of the drive, these settings for P2-01 allow the speed to be controlled remotely using remote pushbuttons connected to digital inputs 2 and 3.
- 2) When Fire mode is enabled (P2-01 = 23), the switching frequency is set to minimum (4kHz) and the following trips are disabled : I.t-trP, OL-br, U-t, O-t, Ph-lb and P-Loss.
- 3) When P2-19 = 2 or 3 in keypad mode, the drive START and STOP is controlled from the hardware enable input (terminal 2). In this case, the START / STOP buttons will have no effect.
- 4) Reverse rotation control using the analog input only works in keypad mode. If P1-12=1, the rotation control only works when P2-19 = 2 or 3. If P2-35 = 2 or 3, the function is disabled.
- 5) When connecting a motor thermistor, connect between terminals 1 & 4, set P2-01 = 6, 10, 11, 12 or 22 (Uses external trip input)

5.7 Digital input configuration – User PID mode (P1-12 = 3)

The following table defines the function of the digital inputs when the drive is in User PID control mode.

P2-01	Digi input 1 function	Digi input 2 function	Digi input 3 function	Analog input function
0..10, 13..16,18	O : Stop (Disable) C : Run (Enable)	No effect	No effect	
11	O : Stop (Disable) C : Run (Enable)	O : PID control C : Preset speed 1	External trip input : O : Trip C : OK	Digital input 1 must be closed to run the drive
12	O : Stop (Disable) C : Run (Enable)	O : Preset speed 1 C : PID control	External trip input : O : Trip C : OK	
17	O : Stop (Disable) C : Run (Enable)	O : PID control C : Bipolar analog input	No effect	
19	O : Stop (Disable) C : Run (Enable)	O : PID control C : 2 nd analog input	No effect	External trip function only possible when bipolar analog input is selected as feedback signal (P3-10=1).
20, 21	O : Stop (Disable) C : Run (Enable)	2 nd digital output : Drive healthy = +24V	No effect	
22	O : Stop (Disable) C : Run (Enable)	2 nd digital output : Drive healthy = +24V	External trip input : O : Trip C : OK	
23	O : Stop (Disable) C : Run (Enable)	O : Normal control C : Fire mode	No effect	

5.5 Digital input configuration – terminal mode (P1-12 = 0)

P2-01	Digi input 1 function	Digi input 2 function	Digi input 3 function	Analog input function	
0	O : Stop (Disable) C : Run (Enable)	O : Bipolar analog input C : Preset speed 1, 2	O : Preset speed 1 C : Preset speed 2	Bipolar analog input	
1	O : Stop (Disable) C : Run (Enable)	O : Preset speed 1 C : Preset speed 2	O : Preset speed 1, 2 C : Preset speed 3	O : Preset speed 1,2,3 C : Preset speed 4	
2	O : Stop (Disable) C : Run (Enable)	Digi input 2	Digi input 3	Analog input	Preset value
		Open	Open	Open	Preset speed 1
		Closed	Open	Open	Preset speed 2
		Open	Closed	Open	Preset speed 3
		Closed	Closed	Open	Preset speed 4
		Open	Open	Closed	Preset speed 5
		Closed	Open	Closed	Preset speed 6
		Open	Closed	Closed	Preset speed 7
Closed	Closed	Closed	Preset speed 8		
3	O : Stop (Disable) C : Run (Enable)	O : Forward C : Reverse	O : Bipolar analog input C : Preset speed 1	Bipolar analog input	
4	O : Stop (Disable) C : Run (Enable)	O : Forward C : Reverse	2 nd Analog input	O : 2 nd analog input C : Preset speed 1	
5	O : Stop (Disable) C : Run (Enable)	O : Forward C : Reverse	Digi input 3	Analog input	Preset value
			Open	Open	Preset speed 1
			Closed	Open	Preset speed 2
			Open	Closed	Preset speed 3
Closed	Closed	Preset speed 4			
6	O : Stop (Disable) C : Run (Enable)	O : Forward C : Reverse	External trip input : O : trip C : OK	Bipolar analog input	
7	O : Stop (Disable) C : Run Forward	O : Stop (Disable) C : Run Reverse	O : Bipolar analog input C : Preset speed 1	Bipolar analog input	
8	O : Stop (Disable) C : Run Forward	O : Stop (Disable) C : Run Reverse	O : Preset speed 1 C : Bipolar analog input	Bipolar analog input	
9	O : Stop (Disable) C : Run Forward	O : Stop (Disable) C : Run Reverse	Digi input 3	Analog input	Preset value
			Open	Open	Preset speed 1
			Closed	Open	Preset speed 2
			Open	Closed	Preset speed 3
Closed	Closed	Preset speed 4			
10	O : Stop (Disable) C : Run Forward	O : Stop (Disable) C : Run Reverse	External trip input : O : trip C : OK	Bipolar analog input	
11	O : Stop (Disable) C : Run (Enable)	O : Bipolar analog input C : Preset speed 1	External trip input : O : trip C : OK	Bipolar analog input	
12	O : Stop (Disable) C : Run (Enable)	O : Preset speed 1 C : Bipolar analog input	External trip input : O : trip C : OK	Bipolar analog input	
13	Normally open (NO) Momentarily close to run	Normally closed (NC) Momentarily open to stop	O : Bipolar analog input C : Preset speed 1	Bipolar analog input	
14	Normally open (NO) Momentarily close to run forward	Normally closed (NC) Momentarily open to stop	Normally open (NO) Momentarily close to run reverse	Bipolar analog input	
15	O : Stop (Disable) C : Run (Enable)	O : Forward C : Reverse	O : Decel ramp 1 C : Decel ramp 2	Bipolar analog input	
16	O : Stop (Disable) C : Run (Enable)	O : Forward C : Reverse	O : Decel ramp 1 C : Decel ramp 2	O : Preset speed 1 C : Preset speed 2	
17	Normally open (NO) Momentarily close to run forward	Normally closed (NC) Momentarily open to stop	Normally open (NO) Momentarily close to run reverse	O : Preset speed 1 C : Keypad mode	
18	O : Stop (Disable) C : Run (Enable)	Digi input 2	Digi input 3	Preset value	O : Terminal mode C : Keypad mode
		Open	Open	Preset speed 1	
		Closed	Open	Preset speed 2	
		Open	Closed	Preset speed 3	
Closed	Closed	Preset speed 4			
19	O : Stop (Disable) C : Run (Enable)	O : Bipolar analog input C : 2 nd Analog input	2 nd Analog input	Bipolar analog input	
20 ¹⁾	O : Stop (Disable) C : Run (Enable)	2 nd digital output : Drive healthy = +24V	O : Bipolar analog input C : Preset speed 1	Bipolar analog input	
21	O : Stop (Disable) C : Run (Enable)	2 nd digital output : Drive healthy = +24V	O : Forward C : Reverse	Bipolar analog input	
22	O : Stop (Disable) C : Run (Enable)	2 nd digital output : Drive healthy = +24V	External trip input : O : trip C : OK	Bipolar analog input	
23 ²⁾	O : Stop (Disable) C : Run (Enable)	O : Normal control C : Fire mode	O : Bipolar analog input C : Preset speed 1	Bipolar analog input	

Notes:

- When P2-01=20, the 2nd digital input is configured as an output, +24V when healthy, 0V otherwise.
- When Fire mode enabled, the switching frequency is set to minimum (4kHz) and the following trips are disabled : l.t-trP, OL-br, U-t, O-t, Ph-lb and P-Loss.

3.4 Control Terminal Connections

The User Control terminals are available via an 11-way pluggable connector. All terminals are galvanically isolated, allowing direct connection to other equipment.




Do not connect mains supply voltages to any terminals other than the User relay output. Permanent damage will otherwise result.

All other inputs will withstand up to 30V dc without damage.

The functionality of the inputs and outputs is user configurable. All operating modes are set up via the parameter set.

Up to 100mA can be sourced from the User +24V output and up to 20mA from the analog output.

The control terminals are defined as follows:



- Terminal 1: +24V, 100mA user output.
- Terminal 2: Digital input 1, positive logic. "Logic 1" when Vin > 8V DC
- Terminal 3: Digital input 2, positive logic. "Logic 1" when Vin > 8V DC
2nd digital output : 0 / 24V, 10mA max
- Terminal 4: 2nd analog input, 11-bit (0.05%). 0..10V, 0..20mA, 4..20mA.
Digital input 3, positive logic. "Logic 1" when Vin > 8V DC.
- Terminal 5: +24V, 100mA reference output (for user with potentiometer).
- Terminal 6: Bipolar analog input, +/-12-bit (0.025%).
Configurable for : 0..24V, 0..10V, -10V...10V, -24V...24V
0V (User GND). Connected to terminal 9
- Terminal 7: Analog output, 8-bit (0.25%). 0..10V, 4..20mA.
- Terminal 8: Analog output, 8-bit (0.25%). 0..10V, 4..20mA.
Digital output : 0 / 24V, 20mA max
- Terminal 9: 0V (User GND). Connected to terminal 7
- Terminal 10: User relay output. Potential free contacts. 30Vdc 5A, 250Vac 6A
- Terminal 11: User relay output. Potential free contacts. 30Vdc 5A, 250Vac 6A


Key control terminal information :

- Maximum input voltage on any terminal 30V dc
- All outputs short circuit proof
- Recommended potentiometer resistance : 10k Ohm
- Digital input response time < 8ms
- Bipolar analog input response time < 16ms. Resolution +/-12 bit (0.025%)
- Second analog input response time < 16ms. Resolution +11-bit (0.05%)
- Analog / Digital output response time < 16ms. Resolution 8-bit (0.25%)

4. Operation

4.1 Managing the keypad

The drive is configured and its operation monitored via the keypad and display



NAVIGATE: Used to display real-time information, to access and exit parameter edit mode and to store parameter changes

UP: Used to increase speed in real-time mode or to increase parameter values in parameter edit mode

DOWN: Used to decrease speed in real-time mode or to decrease parameter values in parameter edit mode

RESET / STOP: Used to reset a tripped drive. When in Keypad mode (see below and P1-12 in the parameter section) is used to Stop a running drive.

START: When in keypad mode, used to Start a stopped drive or to reverse the direction of rotation if bi-directional keypad mode is enabled (see P1-12 in the parameter section)

To change a parameter value press and hold the NAVIGATE key for >1s whilst the drive displays STOP. The display changes to P1-01, indicating parameter 01 in parameter group 1. Press and release the NAVIGATE key to display the value of this parameter. Change to the required value using the UP and DOWN keys. Press and release the NAVIGATE key once more to store the change. Press and hold the NAVIGATE key for >1s to return to real-time mode. The display shows STOP if the drive is stopped or the real-time information (eg speed) if the drive is running.

To change parameter group, ensure that extended menu access is enabled then press NAVIGATE, simultaneously pressing and releasing the UP key until the required parameter group is displayed.

To reset factory default parameters, press UP, DOWN and STOP for >2s. The display shows "P-DEF". Press the STOP button to acknowledge and reset the drive.

4.2 Easy startup

1. Connect motor to drive, checking star/delta connection for the voltage rating
2. Enter motor data from motor nameplate :
P1-07 = motor rated voltage
P1-08 = motor rated current
P1-09 = motor rated frequency
3. Enable the drive. The drive automatically carries out a static Auto-tune

To operate in terminal mode (default setting), connect a switch between terminals 1 and 2 on the user terminal block. Connect a potentiometer (2k2 to 10k) between terminals 5, 6 and 7 with the wiper connected to pin 6.

Close the switch to enable the drive. Adjust speed with the potentiometer.

To operate in keypad mode, set P1-12 = 1 (uni-directional) or 2 (bi-directional). Place a wire link or switch between terminals 1 and 2 on the user terminal block to enable the drive. Now press START. The drive enables at 0Hz. Press the UP button to increase speed. Press the STOP button to ramp to stop.

The desired target speed can be preset by pressing STOP whilst the drive is stopped. When the START key is subsequently pressed, drive will then ramp to this speed.

Key Parameters

- Adjust the maximum / minimum speed limit using P1-01 and P1-02
- Adjust the acceleration and deceleration times using P1-03 and P1-04

5.3 Group 3 : User feedback control (PID control)

P3-01	User PID controller Proportional Gain	0.1 ... 30.0	2	Higher value used for high inertia. Too high a value gives instability.
P3-02	User PID controller Integral time constant	0.0s ... 30.0s	1s	Higher value gives slower, more damped response.
P3-03	User PID controller Differential time constant	0.00s ... 1.00s	0.00	Set to zero (disabled) for most applications.
P3-04	User PID controller operating mode	0: Direct 1: Inverse	0	Most applications use 'Direct' mode. If an increasing feedback signal should increase the speed of the motor, set to 'Inverse' mode
P3-05	User PID controller reference select	0: Digital 1: Analog	0	Sets the source for the PID control reference signal. When set to 1, the bipolar analog input is used
P3-06	User PID digital reference	0 ... 100%	0.0 %	Sets the preset reference used when P3-05 = 0
P3-07	User PID controller output high limit	P3-08 to 100% of control range	100%	Preset PID controller output upper (speed) limit. 100% = P1-01
P3-08	User PID controller output low limit	0 to P3-07	0	Preset PID controller output lower (speed) limit. 100% = P1-01
P3-09	User PID output limit control	0: Digital output limits 1: Analog upper limit 2: Analog lower limit 3: PID output + Bipolar Analog input	0	When set to 1 or 2, the bipolar analog input is used to vary the PID output limit between P1-02 and P1-01. When set to 3, the bipolar analog input value will be added to the PID output.
P3-10	User PID feedback select	0: 2 nd Analog input 1: Bipolar analog input	0	This parameter selects feedback signal source.

5.4 Group 4 : VTC control functions

P4-01	Reserved		0	This parameter is reserved
P4-02	Motor parameter auto-tune	0: Disable 1: Enable	0	When set to 1, drive immediately carries out a static (non-rotating) motor parameter measurement operation to configure the motor parameters. No hardware enable is required. Parameter P1-07, P1-08 and P1-09 must be set correctly according to the motor nameplate before enabling this function. Auto-tune runs automatically on first enable after parameter default operation and P1-08 was changed.

Fire Mode

The fire mode function is provided to ensure that the Optidrive VTC can continue to operate without interruption when fire mode is activated. Fire mode disables non-critical trip functions so that the Optidrive will continue to operate until either the drive itself, the motor or the cabling is destroyed by the fire.

Since normal operation of the Optidrive is overridden when fire mode is active, it is possible that damage to the ventilation system may result from over-pressure. It is also possible that the Optidrive may itself fail or cause damage to the motor.

Invertek Drives Ltd accepts no liability for damage to the Optidrive VTC itself, other components or equipment, HVAC installations, property or injury to personnel when operated in Fire mode. In no event shall Invertek Drives Ltd be liable to any party for loss or damage, whether direct or indirect as a result of operating the drive in Fire Mode.

P2-26	Modbus RTU baud rate	9600bps to 115200bps	115.2	Modbus network communication baudrate.
P2-27	Drive communication address	0: Disable 1..63	1	Distinct drive address used for all drive serial communications.
P2-28	Master / Slave mode select	0: Slave mode 1: Master mode	0	When in Master mode, the drive transmits its operational status via the serial data link. Used to control slave drives via the serial link. P2-27 must be 1 for Master mode.
P2-29	Digital speed reference preset scaling factor	0..500%, steps of 0.1%	100.0%	The digital speed reference input to the drive is scaled by this factor. Operates on references originating from the serial data link. Can be used as an electronic gearbox for Master / Slave applications. This preset value only works when P2-35=1(see P2-35 for details). And it is usually used in a Master / Slave network application.
P2-30	Bipolar analog input format	0..24V, 0..10V, -10..10V, -24..24V	0..24V	Configures the analog input format to match that of the reference signal.
P2-31	Bipolar analog input scaling	0..500.0%	100.0%	Scales the analog input by this factor. Set to 200% to give full speed range control with 0..5V input (when P2-30 = 0..10V)
P2-32	Bipolar analog input offset	-500.0...500.0%	0.0%	Sets the offset from zero at which speed starts to ramp up. Value is "% of the full scale input voltage.
P2-33	2 nd analog input format	0 / 24V (digital input) 0..10V, 4..20mA, 0..20mA	0 / 24V	Determines the format of the 2 nd analog input. Selecting 0 / 24V sets up the input as a digital input.
P2-34	2 nd analog input scaling	0..500.0%	100.0%	Scales the 2 nd analog input by the factor set in this parameter.
P2-35	Digital speed reference scaling control	0: Disabled (no scaling) 1: Scaling set by preset value in P2-29 2: Slave speed scaled by preset value in P2-29, then bipolar analog input added as offset 3: Slave speed scaled by preset value in P2-29 and by bipolar analog input	0	Only active in keypad control mode and usually used in a Master/Slave network application. When P2-35 = 1, actual speed = Digital speed * P2-29. When P2-35 = 2, actual speed = (Digital speed x P2-29) + bipolar analog input Max analog input is equal to P1-01 When P2-35 = 3, actual speed = (Digital speed x P2-29) x bipolar analog input Analog input scales 0% ... 200%
P2-36	Analog output format	0..10V 4..20mA 10..0V 20..4mA	0..10V	Determines the analog output format. Min load impedance in voltage mode 1k Ohm. Max load impedance in current mode 1k Ohm.
P2-37	Extended menu access code define	0..9999	101	Defines the extended menu access code used in P1-14.
P2-38	Parameter Lock	0: Unlocked 1: Locked	0	When locked, all parameter changes are prevented.
P2-39	Hours run clock	0 to 99999 hours	Read only	Indicates the number of hours the drive has been running since new.
P2-40	Drive type / rating	" 0.37" "0 230" : 3 ^{GV} 230V 0.37kW "HP 20" "1 460" : VTC, 460V 20HP	Read only	Indicates drive power rating, type code and voltage rating. Drive type code indicates 3GV (0), VTC (1) or other drive type

5. Drive configuration

5.1 Group 1 : Basic Parameters

Par.	Description	Range	Default	Explanation
P1-01	Max speed limit	P1-02 to 120Hz max.	50 Hz	Sets the maximum speed limit. Display of Hz or rpm dependent on P1-10.
P1-02	Min speed limit	0 to P1-01	0 Hz	Minimum speed limit. Hz or rpm display depending on P1-10.
P1-03	Accel ramp time	0 to 3 000s	30.0s	Time to ramp from 0 to rated frequency (P1-09)
P1-04	Decel ramp time	0 to 3 000s	30.0s	Time to ramp from rated frequency (P1-09) to 0. When P1-04 = 0, the ramp is varied dynamically to give the fastest possible ramp to STOP.
P1-05	Stop mode select	0: Ramp to stop 1: Coast to stop 2: Ramp to stop	0	P1-05 = 0 : If the supply is lost, the drive will try to continue running by reducing load speed, using the load as a generator If P1-05 = 2 : if the supply is lost, the drive ramps on 2nd decel ramp P2-25 to stop; if P2-25 = 0, drive coasts to stop.
P1-06	Energy Optimiser	0: Disabled 1: Enabled	0	When enabled, automatically reduces applied motor voltage on light load. Used in V/F mode only.
P1-07	Motor rated voltage	0V, 20V to 250V 0V, 20V to 500V 0V, 20V to 575V	230V 400V (460V) 575V	Set to motor rated voltage from nameplate. When in V/F mode, P1-07 = 0 gives faster deceleration ramp without over-voltage trip
P1-08	Motor rated current	20% to 100% of drive rated current	Drive rating	Set to motor rated current from nameplate (Amps)
P1-09	Motor rated frequency	25 to 120Hz	50Hz (60Hz)	Set to motor rated frequency from nameplate (Hz).
P1-10	Motor rated speed	0 to 7 200rpm	0	When 0, drive operates in Hz. Upper limit set to 60 x P1-09. This value usually can be found in the motor nameplate.
P1-11	Preset speed 1	-P1-01 to P1-01	50Hz (60Hz)	Sets jog / preset speed at which drive runs when preset speed 1 selected via digital inputs (see also P2-01)
P1-12	Terminal / Keypad control of drive	0: Terminal control 1: Keypad control (Fwd only) 2: Keypad control (Fwd and Rev) 3: Enable User PID 4: Modbus control	0	0 : Terminal control 1 : Uni-direction keypad control. 2 : Bi-directional keypad control. Keypad START button toggles between forward and reverse. 3 : User PID (feedback control) active, setup in parameter group 3. 4 : Drive controlled via integrated Modbus RTU interface.
P1-13	Trip Log	Last 4 trips stored	-	Latest 4 trips stored. Most recent displayed first.
P1-14	Extended Menu Access code	0 to 30 000	0	Permits access to extended menu when P1-14 = P2-37. Default access value = 101.

Notes:

- Default parameter values for Horse Power rated drives are shown in brackets

5.2 Group 2 : Extended Parameters

Par.	Description	Range	Default	Explanation
P2-01	Digital input function select	0 to 23	0	Defines the function of the digital inputs. See sections 5.5 ... 5.7 on pages 16...18 for more details.
P2-02	Preset speed 2	-P1-01 to P1-01	0 Hz	Sets jog / preset speed 2
P2-03	Preset speed 3	-P1-01 to P1-01	0 Hz	Sets jog / preset speed 3
P2-04	Preset speed 4	-P1-01 to P1-01	0 Hz	Sets jog / preset speed 4
P2-05	Preset speed 5	-P1-01 to P1-01	0 Hz	Sets jog / preset speed 5
P2-06	Preset speed 6	-P1-01 to P1-01	0 Hz	Sets jog / preset speed 6
P2-07	Preset speed 7	-P1-01 to P1-01	0 Hz	Sets jog / preset speed 7
P2-08	Preset speed 8	-P1-01 to P1-01	0 Hz	Sets jog / preset speed 8
P2-09	Skip frequency	P1-02 to P1-01	0	Centre point of skip frequency band set up in conjunction with P2-10.
P2-10	Skip frequency band	0 to P1-01	0 (disable)	Width of skip frequency band centred on frequency set in P2-09.
P2-11	Analog output function select	(Digital output mode) 0: Drive enabled 1: Drive healthy 2: Motor at target speed 3: Motor speed > 0 4: Motor speed > limit 5: Motor current > limit 6: 2 nd analog input > limit (Analog output mode) 7: Motor speed 8: Motor current 9: Motor power (kW)	7	For values 0 to 6, analog output functions as a digital output. (0V or 24V output) The control limit used for settings 4, 5 and 6 is defined in P2-12(h) and P2-12(L). For values between 7 and 9, the output is analog signal, operating between 0..10V or 4..20mA. (as set in P2-36) Full scale analog output results at max speed (P1-01), 2x rated motor current (P1-08) or 1.5x rated power of the drive.
P2-12 (h)	Digital output control high limit	Speed : 0..100% (100% = max speed) Current : 0..200% (100% = rated current) PID feedback : 0..100% (100% = max 2 nd analog input)	100%	Digital output state set to logic 1 when selected value in P2-11 larger than this limit. Limit in P2-12 relates to speed if P2-11 = 4, to motor current if P2-11 = 5 or to the PID feedback value (2 nd analog input) if P2-11=6.
P2-12 (L)	Digital output control low limit	0 ... P2-12(h)	100%	Digital output state back to logic 0 when selected value in P2-11 less than or equal to this limit. (P2-11 = 4,5 or 6)
P2-13	User relay output function select	0: Drive Enabled 1: Drive healthy 2: Motor at target speed 3: Motor speed > 0 4: Motor speed > limit 5: Motor current > limit 6: 2 nd analog input > limit	1	If P2-15 = 0 (Normally Open), the relay contacts are closed when the selected condition is fulfilled. If P2-15 = 1 (Normally Closed), the relay contacts are open when the selected condition is fulfilled.
P2-14 (h)	User relay output control high limit	Speed : 0..100% (100% = max speed) Current: 0..200% (100% = rated current) PID feedback : 0..100% (100% = max 2 nd analog input)	100%	User relay output closes (P2-15=0) when selected value in P2-13 larger than this limit. Limit in P2-14 relates to speed if P2-13 = 4, to motor current if P2-13 = 5 or to the PID feedback value (2 nd analog input) if P2-13=6
P2-14 (L)	User relay output control low limit	0 ... P2-14(h)	100%	Digital output state back to logic 0 when selected value in P2-13 less than or equal to this limit. (P2-13 = 4,5 or 6)
P2-15	Relay output mode	0: Normally Open (NO) 1: Normally Closed (NC)	0 (N.O.)	The drive must be powered up for the relay contacts to be closed.
P2-16	Standby mode wake-up speed	0..100%	0.0%	Drive will wake up from standby mode if the speed reference exceeds this limit. 100% = P1-01.

P2-17	Start mode select	Edgr-r : Close digital input 1 after power up to start drive Auto-0 : drive runs whenever digital input 1 is closed Auto-1...5 : as Auto-0, except 1..5 attempts to restart after a trip	Auto-0	When set to Edge-r, if drive is powered up with digital Input 1 closed (enabled), drive will not run. The switch (digital input 1) must be opened and closed after power up or after resetting a trip for the drive to run. When set to Auto-0, drive will run whenever digital input 1 is closed (if not tripped). Auto-1...5 makes 1...5 attempts to automatically restart after a trip (20s between attempts in default). Drive must be powered down to reset the counter.
P2-18	Spin Start Enable	0: Disable 1: Enable	0	When enabled, drive detects motor speed and starts driving the motor from this speed. (the motor speed can be in both direction: forward or reverse) A short delay of approx 1s will result after enabling the drive before speed is detected.
P2-19	Keypad restart mode	0: Minimum speed 1: previous speed 2: Min-speed (Auto-r) 3: prev. speed (Auto-r)	1	If set to 0 or 2, drive will always start from minimum speed. If set to 1 or 3, drive ramps up to the operating speed prior to the last STOP command. If set to 2 or 3, the status of digital input 1 controls drive to start or stop. The start and stop button will not work in this case.
P2-20	Standby mode	0: Disable 1 ... 60s	0	If P2-20 >0, drive enters standby mode (disables output) if minimum speed (P1-02) is maintained for the time specified in P2-20. Drive wakes up automatically if the speed ref is greater than P1-02 or the value set in P2-16, whichever is the higher.
P2-21	Display scaling factor	0.000 to 30.000	0.000	Disabled if set to zero. The variable selected in P2-22 is multiplied by this factor and displayed as a real-time value on the drive, in addition to speed, current and power.
P2-22	Display scaling source	0: 2 nd analog input 1: Speed	0	Selects the variable to be scaled by the factor set in P2-21.
P2-23	Brake circuit enable	0: Disable 1: Enable + lo power 2: Enable + hi power 3: Enable, no protection	0	Enables the internal brake chopper Overload protection in software when set to 1 or 2. See rating tables for resistor sizing guidelines.
P2-24	Effective switching frequency	S2 230V : 4..32kHz S2 400V : 4..32kHz S3 400V : 4..24kHz S4 400V : 4..24kHz S5 400V : 4..16kHz S6 400V : 4..16kHz * Max limit dependent on power rating	16 kHz 8 kHz 4 kHz 4 kHz 4 kHz 4 kHz	Effective power stage switching frequency. Improved acoustic noise and output current waveform results from increasing switching frequency, but at the expense of increased losses within the drive. "Auto" selects minimum possible switching frequency for the speed range selected (when "Auto" set, P2-24 = 16x P1-01).
P2-25	Second deceleration ramp time	0s ... 3 000s	0s	Selected automatically on mains loss if P1-05 = 2. Can also be selected via digital inputs during operation. (see section 5.5 & 5.6)