


OMNIDRIVE

Circulator Pump Motors

Single Phase Motors - ODP



Type 2A / 2B



Type 2C



Type 2C

- Mounting Bracket
- Sleeve Bearing with Oil Ports
- Open Drip-Proof
- 1800 RPM
- Single Phase
- Ball Bearing

- Replacements for Many Popular OEM Motors such as: Armstrong, Bell & Gossett & Taco

• Please Note:

Type '2A' 4.67" B.C.D. fits # 2 Bearing Assembly

Type '2B' 5.00" B.C.D. fits # 3 & 4 Bearing Assembly

Type '2C' 5.875" B.C.D. fits # 5, 6, 7 Bearing Assembly

Stock #	HP	Volts	Amps.	Type	Bearing	Rotation	Replaces
SS1350	1/12	115	2.50	2A	Ball	CWSE	R1350, 805316-010, 831000-61, 111034
SS1355	1/6	115	3.80	2A	Ball	CWSE	-----
SS1352	1/6	115	3.80	2B	Ball	CWSE	R1352, 817025-001, 831001-061, 111031
SS1354	1/4	115	4.60	2B	Ball	CWSE	R1354, 817025-007, 831002-061, 111040
SS1444	1/4	115	4.60	2C	Ball	CCWSE	R1444, 816141-001
SS1356	1/3	115	6.00	2B	Ball	CWSE	R1356, 817025-013, 831003-061, 111042
SS1446	1/3	115	6.00	2C	Ball	CCWSE	R1446, 816141-002
SS1459	1/2	115-208/230	5.70 / 3.00 - 2.90	2C	Ball	REV.	R1459, 811757-001, 111044
SS1462	3/4	115-208/230	8.20 / 4.70 - 4.20	2C	Ball	REV.	R1462, 811757-002, 033, 111047



UNIVERSAL ELECTRIC MOTORS

DIVISION OF 1279311 ONTARIO INC.

6200 Dixie Road, Unit 1, Mississauga, Ontario, L5T 2E1

Tel: (905) 670-3380 - Toll free: 1-877-670-3380 - Fax: (905) 670-7637

WWW.UEM.CA - INFO@UEM.CA

